

# 0 - 30V, 2A Dual Power Supply with Automatic Overload Protection Scientech 4075



**Scientech 4075 DC Dual Power Supply** is designed as a Constant Current (CC) and Constant Voltage (CV) source for use in laboratories, industries and field testing. With compact size, light weight and low power loss, it provides DC output voltages for Analog and Digital testing.

A special automatic overload (current) protection circuit limits the maximum current to 2 A. Two displays (one 3-digit display for voltage & other 3-digit for current) are used to read the values. These two can be switched simultaneously for either of the DC outputs.

Scientech 4075 has excellent line and load regulation and is provided with protective circuits to ensure trouble free operation.

### **Features**

- Pre-Regulator based design
- Floating DC Supply Voltages
- Dual DC:2x0-30V/2A
- Automatic Overload (Current protection)
- Constant Voltage & Constant Current operation

- Digital display for Voltage and Current
- Adjustable Current limiter
- Excellent Line & Load Regulation
- Low Ripple Voltage



# 0 - 30V, 2A Dual Power Supply with Automatic Overload Protection Scientech 4075

# **Technical Specifications**

DC Output :  $2 \times 0 - 30 \text{ V}$ , 2 A continuously variable by means of coarse and fine controls

Current limit : 100 mA - 2 A continuously adjustable

Resolution : Voltage: 100 mV

Current: 10 mA

 $Internal\,Resistance \hspace{1.5cm} :\hspace{.5cm} \leq 15\,m\Omega$ 

Stability : 2.5 mV at 30 V/2A

Recovery Time :  $\leq 50~\mu s$ 

Load Regulation :  $\pm (0.05\% + 10 \text{ mV})$ 

Line Regulation :  $\pm (0.05\% + 10 \,\text{mV})$ 

Temperature Coefficient :  $\pm (0.05\% + 5 \text{ mV}/^{\circ}\text{C})$ 

Ripple & Noise :  $\leq 1 \text{ mVrms}$ 

Display : 3 digit for voltage & 3 digit for current LED indication for Voltage & Current

Accuracy :  $\pm (1\% + 1 \text{ digit})$ 

Over Range Indication : Glowing 'ORA' and 'ORB' LEDs indicate Overload

## **General Information**

Both outputs are floating.

Built-in Overheat, Over Voltage and Short Circuit protection.

#### Insulation

Between chassis & output terminals > 10 M $\Omega$  at 100 V DC

Between chassis & AC plug > 50 M $\Omega$  at 500 V DC

Power Supply :  $230 \text{ V}, \pm 10\%, 50/60 \text{ Hz}$ 

Operating Temperature :  $0-40^{\circ}\text{C}$ , 80% RH

Dimension (mm) :  $W 285 \times D410 \times H88$ 

Weight : 4.75 Kg approximately

Product Tutorial : Online www.ScientechLearning.com

**Included Accessories** 

Mains cord : 1 no.